# WaveTester / WaveSource 850/1300/VFL Test Kit

KIT-WT-WSMDVxx (see connector options below)

#### Overview

Many fiber optic network bids and Requests For Quote (RFQ) are citing cabling standards to specify the set of guidelines (such as fiber length) that the network installer must follow during the network installation. Adherence to such standards is meant to ensure the quality of the installation and guarantee that the network will perform as it was designed.

The process of testing a network installation to ensure its adherence to specified standards is called certification, and often requires hard-copy documentation as proof of adherence to standards.

The *WaveTester / WaveSource 850/1300/VFL Test Kit* contains the tools necessary for certifying fiber optic links against a myriad of popular cabling standards in multimode networks.

The *WaveTester optical power meter* is multimode and singlemode ready, and can store reference values for all wavelengths used for optical loss measurements. Up to 200 fiber runs may be stored, and serially downloaded to a PC for report generation using our OWL Reporter software.

The *WaveSource 850/1300/VFL* is a multimode light source. Its dual wavelength outputs (850 nm & 1300 nm) are temperature-stabilized for accurate measurements. A Visual Fault Locator is also included for near-end visual fault location and visual fiber identification. Two connector options are available (ST or SC).



### Features

Certification of multimode fiber links at 850 nm and 1300 nm

Auto-test functions store references and data points automatically

Data storage for up to 200 data points

USB interface for continuous data logging, report printing, or data downloading

Multimode Fiber Certification Test Kit

OWL Reporter software for printing formatted fiber certification reports

Measurement modes include absolute (for optical power) or relative (for optical loss)

Near-end visual fault location

Visual fiber identification

Selectively view, delete or resample data points

#### Supported Cabling Standards:

EIA/TIA 568-B ISO/IEC 11801 10-Gigabit Ethernet

1000Base-SX 1000Base-LX 100Base-FX

10Base-FB 10Base-FL FDDI

ATM-155 ATM-622 Fibre Channel

Token Ring

#### Additional Power Meter Calibrated Wavelengths:

1310nm 1550nm



Patch cables are available for an additional charge. Contact OWL for more information.

## Kit Contents

Power Meter: WaveTester

Light Source: WaveSource 850/1300/VFL
Accessories: OWL Reporter software

Product manuals Download cable 9-volt batteries NIST certificate Carrying case

Protective rubber boots



O. W. L. MANUFACTURER OF QUALITY OPTICAL FIBER TEST EQUIPMENT





Sold at LANshack.com sales@lanshack.com 888-568-1230

# WaveTester / WaveSource 850/1300/VFL Test Kit

KIT-WT-WSMDVxx (see connector options below)

# Specifications WaveTester Optical Power Meter

Detector Type	InGaAs
NIST Traceable Wavelengths	850 nm, 1300nm, 1310nm 1550nm
Measurement Range	+5 to -60 dBm
Accuracy	±0.15 dB
Resolution	0.01 dB
Connector Type	2.5mm Universal
<b>Data Storage Points</b>	up to 200
<b>Download Data Points</b>	OWL Reporter Software
<b>Power Units Displayed</b>	dBm, dB, μW
Battery Life	250 hrs. (9v alkaline)
<b>Battery Capacity Display</b>	Yes
Backlight	Yes
NIST Traceable	Yes
Auto-shutdown	Yes
<b>Operating Temperature</b>	-10 to 55 C
Storage Temperature	-30 to 70 C
Width	2.75"
Height	4.94"
Depth	1.28"
Weight	154g
Conforms to the Harmonized 61326-1 and EN 61010-1.	European Standards EN

Launch Method	LED
Connector	ST or SC
Center Wavelength (850 nm)	850 +30/-10 nn
Center Wavelength (1300 nm)	1300 ±50 nm
Spectral Width (FWHM; 850 nm)	50 nm
Spectral Width (FWHM; 1300 nm	) 180 nm
Output Power	-20.0 dBm
Initial Accuracy	0.1 dB
Fiber Type	multimode
Battery Capacity Display	Yes
Operating Temperature	-20 to +70° C
Storage Temperature	-40 to +85° C
Width	2.75"
Height	4.94"
Depth	1.28"
Weight	154g
Visual Fault Locator Specification	ons
Launch Method	Laser
Center Wavelength	650 nm
Output Power	-2.0 dBm
Fiber Type	multimode
Conforms to the Harmonized Europear 61326-1 and EN 61010-1.	n Standards EN





